YDBH0.66-60III

YDBH0.66-60III Low voltage current transformer(the electric power uses)

Features

- 100A~2000A 5A 1A 0.2 0.2S 0.5 0.5S The primary current is 100A~2000A,while the secondary current is 1A,5A. The products line covers accuracy of 0.2 0.2S 0.5 0.5S.
- Vacuum-heat treatment for the iron core achieves excellent performance and stable precision.
- PC The outer case is made of PC materials which is non-flammable. the performance is reliable and the product is safe for use.
- Easy installation; Fixed by metal slice.
- GB20840.2-2014 The performance meets the standard of GB 20840.2-2014 “Current Transformer”.

Matters needing attention

- 0.66kV The use does not surpass 0.66kV in the rated voltage the AC-circuit, the long lasting work electric current does not surpass the rated value.
- P1 P2 S1 S2 The product is a minus polarity, The first connection wiring symbol is P1 P2,the corresponding secondary current wiring symbol is S1 S2.
- S1 S2 Measuring instruments connected to S1 S2 terminals, two times windings outside return route metering equipment total impedance(including wiring) should not be super high rated load.
- The current transformer refuses in the movement two times separation.
- In order to ensure the measurement accuracy, the copper bar should be installed in the middle.

Specification And Technical parameter

Model	Parameter (A)	Rated load (VA)

Addr YADA Industrial Park,Gaopugang ,Heyuan City, Guangdong
TEL 86-762-3493888 FAX 86-762-3493912 POST 517000
http://www.yada.com.cn. E-mail: market@yada.com.cn