YM-DD16K2-W1 Ḥ ˥"ḤỌ ĺ 16 ˆ ˜ Ḥ„ ˇ 2 ₪ ₹ └Â ⁘ ᵝ ╕
Ḥ„ ˇ ƀˇ ŵ Ƅʊڜ ı "Ḥ ɒˇ Â

YM-DD16K2-W1 Remote signalling and Remote control unit is equipped with 16-channel passive digital input signal acquisition and 2 relay output control.The remote signal acquisition and remote control operation can be realized by the upper computer, which is a hybrid intelligent component, which can be widely used.

˜ ' 16 ˆ Ḥ„ (˜)
Input: 16-channel switching signal (passive dry contact input)
₪ ₹ ' AC250Vˇ 5A
Relay output contact capacity: AC250Vˇ 5A
ˆ ' AC85~265V or DC85~330V DC20~60V ╕
Power supply AC85~265V or DC85~330V or DC20~60V Optional
˩' / ˜ / ₹ ' AC3.0kV/min·1mA
Insulation voltage: Between power supply/input/output: AC3.0kV/min·1mA
' Ó100Mq
Insulation resistance: Ó100Mq
' ' MODBUS RTU
Communication port: MODBUS RTU
ڜشحشم 1~246
Address: 1~246
' 1200/2400/4800/9600/19200
Baud rate: 1200/2400/4800/9600/19200
ᵝ ' / Ẽ / N/E/O
Parity bit: N/E/O
' ModBus RTU
Communication protocol: ModBus RTU

:



1-8„ **Terminal 1-8**

19-25„ **Terminal 19-25** **9-18„** **Terminal 9-18**

	run
	communication
Ḥ ˥"Ḥ	Remote remote control unit

9					

Addr YADA Industrial Park,Gaopugang ,Heyuan City, Guangdong
TEL 86-762-3493888 FAX 86-762-3493912 POST 517000
http://www.yada.com.cn. E-mail: market@yada.com.cn

Addr YADA Industrial Park,Gaopugang ,Heyuan City, Guangdong
TEL 86-762-3493888 ě